

12

EUROPEAN PATENT APPLICATION

21 Application number: 89303042.9

51 Int. Cl. 4: H 04 N 5/232
 G 03 B 3/10

22 Date of filing: 28.03.89

30 Priority: 29.03.88 JP 77545/88

43 Date of publication of application:
 04.10.89 Bulletin 89/40

84 Designated Contracting States: DE FR GB NL

71 Applicant: SONY CORPORATION
 7-35 Kitashinagawa 6-Chome Shinagawa-ku
 Tokyo 141 (JP)


72 Inventor: Yoshida, Masanobu c/o Patents Division
 c/o Sony Corporation 6-7-35 Kitashinagawa
 Shinagawa-ku Tokyo 141 (JP)

74 Representative: Thomas, Christopher Hugo et al
 D Young & Co 10 Staple Inn
 London WC1V 7RD (GB)

54 Automatic focus control apparatus.

57 An automatic focus control apparatus (1) makes use of the chromatic aberration of a lens (2), such as a zoom lens (2) of a video camera, to detect focus position information on the basis of amplitude values of respective primary colour signals derived by an image pick-up element (3), and hence control the focus of the lens (2).

FIG. 2



Description

AUTOMATIC FOCUS CONTROL APPARATUS

This invention relates to automatic focus control apparatus. Embodiments of the invention are particularly, but not exclusively, suitable for use in auto-focus television cameras.

Apparatus that detects the focus of a lens by detecting the contrast of a picked-up image is known (see Japanese patent application no. 62/146628). Such apparatus uses the fact that the picked-up image has the best contrast when it is in focus. This focused position of a lens will hereinafter be referred to as the properly-focused position.

Accordingly, as shown in Figure 1, a properly-focused position P for an object can be detected by detecting the position of the lens at which an output signal from an image pick-up element has a maximum amplitude value.

In a television camera using this principle, the lens is moved away from its position closest to the object while sequentially detecting the amplitude values of the output signals, whereby the television camera can capture the properly-focused position P by detecting the position at which the change from the increase to decrease takes place in the amplitude value. Therefore, by adjusting the position of the lens on the basis of the detected result, it is possible to focus the object properly.

Moreover, in the television camera, once the properly-focused state has been established, the position of the lens is vibrated back and forth around the properly-focused position P by a predetermined amount P_w (hereinafter, this vibrating movement is referred to as wobble) so that any change in the properly-focused position P can be detected regardless of the change of the properly-focused position P due to movement of the object. Thus, the position of the lens is adjusted on the basis of the detected result, thus making it possible to follow movement of the object while maintaining the properly-focused state.

This kind of auto-focused apparatus, however, has a defect. Thus because the position of the lens is wobbled around the properly-focused position P by the predetermined amount P_w , the picked-up image is also wobbled unnaturally, resulting in the quality of the picked-up image being deteriorated.

To solve this problem it has been proposed to wobble the position of the image pick-up element instead of the position of the lens. In this case, although the picked-up image can be prevented from being unnaturally wobbled, and the properly-focused condition can be achieved, a driving mechanism such as an actuator is required to wobble the image pick-up element, and in consequence the overall arrangement of the auto-focus apparatus becomes complicated.

Moreover, if the image pick-up element is wobbled as described above, the picked-up image is repeatedly caused to lose focus, so again the image quality is deteriorated. Accordingly, the image pick-up element has to be wobbled at sufficiently

low frequency for the deteriorated quality of picked-up image not to be conspicuous to a viewer, but it is not then possible to maintain focus on a fast-moving object.

According to the present invention there is provided an automatic focus control apparatus characterized by:

lens means having chromatic aberration;

means for converting an optical signal obtained through said lens means to an electrical signal; means for processing said electrical signal to obtain a plurality of primary colour signals;

means for detecting the amplitude level of each of said primary colour signals;

means for generating a control signal according to levels of said primary colour signals derived from said level detecting means; and

means for controlling the position of said lens in response to said control signal.

The invention will now be described by way of example with reference to the accompanying drawings, throughout which like parts are referred to by like references, and in which:

Figure 1 is a graph used to explain a known auto-focus apparatus;

Figure 2 is a schematic in block diagram form of an auto-focus apparatus embodying the present invention; and

Figures 3 to 6 show a diagram, a graph, a table and a flow chart, respectively, used to explain the operation of the apparatus of Figure 2.

Figure 2 shows an embodiment of auto-focus apparatus 1 for use with a television camera, the apparatus comprising a zoom lens 2, in which L_1 and L_2 designate lens groups thereof, which picks up an image of an object (not shown). The zoom lens 2 is arranged to have a predetermined, very small amount of a chromatic aberration, so that it will not deteriorate the quality of the picked-up image.

As shown in Figure 3, when green light L_G is focused on a target screen H_t of an image pick-up element 3 (Figure 2), blue light L_B is focused at a position displaced towards the zoom lens 2 (or lens L_3) from the target screen H_t by a predetermined very short distance P_B (this position will hereinafter be referred to as a forward focus side) while red light L_R is focused at a position displaced in the opposite direction, that is, towards the image pick-up element 3, from the target screen H_t by a predetermined very short distance P_R (this position will hereinafter be referred to as a backward focus side). In this case, P_B is selected to be equal to P_R .

With this arrangement, as shown in Figure 4, when amplitude values of blue, green and red signals S_B , S_G and S_R from the image pick-up element 3 are detected by varying the focus position of the zoom lens 2 towards the forward and backward focus sides, the green signal S_G has the maximum signal level at the properly-focused position P of green light L_G , while the blue and red signals S_B and S_R have the

maximum signal levels at the forward and backward sides with respect to the properly-focused position P as represented by A and D in Figure 4, respectively.

The properly-focused condition can therefore be achieved by adjusting the position of the zoom lens 2 in such a manner that the amplitude value of the green signal S_G becomes larger than those of the blue and red signals S_B and S_R .

To be more specific, referring back to Figure 2, in the auto-focus apparatus 1, the output signal from the image pick-up element 3 is supplied through a preamplifying circuit 4 to a signal processing circuit 5, in which it is processed to form the blue, green and red signals S_B , S_G and S_R which are supplied to a matrix circuit 6, in which they are processed to form a luminance signal Y and two colour difference signals S_{R-Y} and S_{B-Y} .

Band-pass filter circuits 7A, 7B and 7C, each of which has a frequency range of from 500 kHz to 2 MHz, receive the blue, green and red signals S_B , S_G and S_R and extract alternating current components therefrom. Detecting circuits 8A, 8B and 8C, connected to the band-pass filter circuits 7A, 7B and 7C, respectively, envelope-detect the output signals from the band-pass filter circuits 7A, 7B and 7C, respectively. The amplitude value signals of the colour signals S_B , S_G and S_R therefrom are supplied to a selector switch 9. The output of the selector switch 9 is supplied to an auto-focus control circuit 10 through an analogue-to-digital (A/D) converter 12. The colour signals S_B , S_G and S_R are also supplied to a selector switch 11 whose output is converted by an A/D converter 13 to a digital signal which is supplied to the auto-focus control circuit 10.

The auto-focus control circuit 10, which comprises a computer processing circuit such as a microprocessor, supplies a switching signal Sc_1 to the selector switches 9 and 11. Thus, the auto-focus control circuit 10 is sequentially supplied with the output signals of the detecting circuits 8A, 8B and 8C through the selector switch A/D converter 12, and also with the colour signals S_B , S_G and S_R through the selector switch 11 and the A/D converter circuit 13.

Accordingly, in the auto-focus control circuit 10, the amplitude values of the colour signals S_B , S_G and S_R from the A/D converter 12 can be detected, while the signal levels of the colour signals S_B , S_G and S_R from the A/D converter 13 can also be detected.

The image pick-up element 3, the preamplifying circuit 4, the signal processing circuit 5 and the matrix circuit 6 form image pick-up means that picks up an image of an object by means of the zoom lens 2. On the other hand, the band-pass filter circuits 7A, 7B and 7C, the detecting circuits 8A, 8B, and 8C, the selector switch 9 and the A/D converter 12 form amplitude value detecting means that detects the amplitude values of the colour signals S_B , S_G and S_R derived from the image pick-up means.

Moreover, the auto-focus control circuit 10 includes a table of values stored in internal memory (ROM) (not shown). In accordance with this table, the amplitude values of the colour signals S_B , S_G and S_R are divided by the signal levels of the correspond-

ing colour signals S_B , S_G and S_R whereby the amplitude values are normalized by the signal levels.

In practice, the amplitude values of the colour signals S_B , S_G and S_R change not only with the position of the zoom lens 2 but also with the hue of the object. However, in this embodiment, since the amplitude values of the colour signals S_B , S_G and S_R are normalized by means of the signal levels of the colour signals S_B , S_G and S_R , an object having a different hue can be properly focused positively when picked up.

Also, the auto-focus control circuit 10 is operative to compare the normalized amplitude values with respect to the respective colour signals S_B , S_G and S_R , and feeds a control signal Sc_2 to a focus position control circuit 15 on the basis of the compared result thereof, thereby controlling the focus of the zoom lens 2.

Figure 5 is a table representing the output characteristics, in which the normalized amplitude values S_B' , S_G' and S_R' of the respective colour signals S_B , S_G and S_R are illustrated in sequential relative level orders, that decrease in the order I, II and III. The table of Figure 5 is stored in the internal (ROM) memory in the auto-focus control circuit 10.

As can be seen in Figure 5, assuming that the zoom lens 2 is set at the properly-focused position P of green light L_G , then the green signal S_G' has the maximum amplitude values as represented by I, and the blue and red signals S_B' and S_R' have amplitude values that are smaller than I but are equal to each other as represented by II.

If on the other hand the zoom lens 2 is set at the position B that is ahead of the properly-focused position P, the amplitude values of the green and red signals S_G' and S_R' are caused to decrease as represented by I and III, while the amplitude value of the blue signal S_B' is caused to increase as represented by I in Figure 5. If the position of the zoom lens 2 is further advanced to the position A away from the properly-focused position P, the amplitude value of the blue signal S_B' is at a maximum, and the amplitude values of the green and red signals S_G' and S_R' tend to decrease as represented by I, II and II, respectively.

Conversely, if the zoom lens 2 is set at the position C that is behind the properly-focused position P, the amplitude values of the green and blue signals S_G' and S_B' are caused to decrease as represented by I and III, and the amplitude value of the red signal S_R' is caused to increase as represented by I in Figure 5. If the position of the zoom lens 2 is further moved away from the properly-focused position P to the position D, the amplitude values of the blue and green signals S_B' and S_G' tend to decrease, and that of the red signal and S_R' becomes a maximum as represented by III, II and I in Figure 5.

Consequently, the green signal S_G' has the maximum amplitude value in a range from the position B to the position C with respect to the properly-focused position P. If the position of the zoom lens 2 is moved to the positions B and C that are ahead of and behind the properly-focused position P, the blue and red signals S_B' and S_R' have the maximum amplitude values, respectively.

Thus, it is possible for the auto-focus control circuit 10 to determine by the compared result of the normalized amplitude values of the colour signals S_B' , S_G' and S_R' derived from the respective colour signals S_B , S_G and S_R whether or not the focus position of blue light L_B is moved towards the zoom lens 2 side, whether or not the focus position of red light L_R is moved towards the image pick-up element 3 side, or whether or not green light L_G is properly focused at the position P. It is also possible to detect by how much the position of the zoom lens 2 is displaced from the properly-focused position P of green light L_G .

Moreover, in the auto-focus control circuit 10, the focal length of the zoom lens 2 is detected by a zoom amount detecting circuit 17. The thus detected focal length is used to compensate the above-mentioned detected results.

In practice, in the zoom lens 2, the lengths P_B and P_R from the properly-focused position P of green light L_G to the properly-focused positions A and D of blue light L_B and red light L_R are changed with the focal length of the zoom lens 2.

Accordingly, the properly-focused position P can be positively detected, or the displacement of green light L_G from the properly-focused position P can be detected by compensating for the displacement from the properly-focused position P on the basis of the focal length of the zoom lens 2.

Therefore, by adjusting the position of the zoom lens 2 such that the displacement from the properly-focused position P falls below the predetermined value, it is possible to get the object in proper focus even if the object is moving fast, without wobbling the position of the zoom lens 2 or of the image pick-up element 3.

With this embodiment of the invention, since the position of the zoom lens 2 and of the image pick-up element 3 need not be wobbled, the overall arrangement of the apparatus can be simplified, and the quality of the picked-up image can be prevented from being deteriorated.

Thus, the auto-focus control circuit 10 forms a focus position information detecting means that detects focus position information to pick-up the object by means of the zoom lens 2, and by comparing the detected results of the normalized amplitude values of the respective colour signals S_B , S_G and S_R derived by dividing the amplitude values by the corresponding signal levels of the colour signals S_B , S_G and S_R .

With this arrangement, an image of an object is focused on the target screen H_i of the image pick-up element 3 through the zoom lens 2 having the predetermined, very small amount of chromatic aberration and the amplitude values of the colour signals S_B , S_G and S_R thereof are detected via the band-pass filter circuits 7A, 7B, and 7C and the detecting circuits 8A, 8B, and 8C.

Together with the colour signals S_B , S_G and S_R , the amplitude values are supplied through the selecting circuits 9 and 11 and the A/D converters 12 and 13 to the auto-focus control circuit 10 that normalizes them by the signal levels of the colour signals S_B , S_G and S_R thereby producing the compared results. The

compared results are compensated for on the basis of the focal length of the zoom lens 2, and the position of the zoom lens 2 is adjusted on the basis of the thus compensated result.

The operation of the auto-focus control circuit 10 in Figure 2 will now be described with reference to the flow chart of Figure 6.

When the auto-focus operation starts at step 100, the amplitude values of the blue, green and red colour signals S_B , S_G and S_R are respectively normalized by dividing them by the signal levels of the corresponding colour signals S_B , S_G and S_R at steps 101, 102 and 103.

Accordingly, normalized colour signals S_B' , S_G' and S_R' are obtained. Then, the values of the normalized red and green signals S_R' and S_G' are compared at step 104. If the normalized red signals S_R' is greater than the normalized green signal S_G' , then the normalized red signal S_R' is compared with the normalized blue signal S_B' at step 105. If the normalized red signal S_R' is greater than the normalized blue signal S_B' , then it is determined at step 106 that the zoom lens 2 is located at about the position D according to the table of Figure 5. Then, a control signal for moving the focus ring (not shown) of the zoom lens 2 by the amount $2 \times \Delta F$ (F: minimum unit of the movement of the focus ring per one field of the colour signal, for example, 1 mm/field) towards the image pick-up element 3 is generated at step 107, and this control signal is supplied to the focus position control circuit 15 as the control signal S_{C2} at step 108.

If the normalized red signal S_R' is not greater than the normalized blue signal S_B' at step 105, it is determined that this situation does not exist according to the table of Figure 5. Then, the routine goes to NG at step 109 and the focus ring of the zoom lens 2 is not moved.

Going back again to step 104, if the normalized green signal S_G' is equal to the normalized red signal S_R' , then the routine goes to step 110, wherein the normalized green signal S_G' and the normalized blue signal S_B' are compared. If the normalized green signal S_G' is greater than the normalized blue signal S_B' , it is determined at step 111 that the zoom lens 2 is located at about the position C according to the table of Figure 5. Then, a control signal for moving the focus ring of the zoom lens 2 by the amount of ΔF in the direction of the image pick-up element 3 is generated at step 112, and this control signal is supplied to the focus position control circuit 15 as the control signal S_{C2} at step 108.

If the normalized green signal S_G' is not greater than the normalized blue signal S_B' at step 110, then it is determined that this situation does not exist according to the table of Figure 5, and the routine goes to NG at step 109.

Returning to step 104 again, if the normalized green signal S_G' is greater than the normalized red signal S_R' , the routine goes to step 113, wherein the normalized green signal S_G' and the normalized blue signal S_B' are compared. If the normalized green signal S_G' is smaller than the normalized blue signal S_B' , it is determined at step 114 that the zoom lens 2 is located at about the position A according to the

table of Figure 5. Then, a control signal for moving the focus ring of the zoom lens 2 by the amount $2 \times \Delta F$ in the direction of the object is generated at step 115, and this control signal is supplied to the focus position control circuit 15 as the control signal S_{C2} at step 108.

If the normalized green signal S_G' is greater than the normalized blue signal S_B' at step 113, the routine goes to step 116, wherein the normalized red signal S_R' and the normalized blue signal S_B' are compared. If the normalized red signal S_R' is greater or smaller than the normalized blue signal S_B' , it is determined that this situation does not exist according to the table of Figure 5, and the routine goes to NG at step 109. If the normalized red signal S_R' is equal to the normalized blue signal S_B' , it is determined at step 117 that the zoom lens 2 is located at about the position P according to the table of Figure 5. Then, a control signal for stopping the focus ring of the zoom lens 2 is generated at step 118, and this control signal is supplied to the focus position control circuit 15 as the control signal S_{C2} at step 108.

Going back to step 113, if the normalized green signal S_G' equals the normalized blue signal S_B' , it is determined at step 119 that the zoom lens 2 is located at about the position B according to the table of Figure 5. Then, a control signal for moving the focus ring of the zoom lens 2 by the amount ΔF to the direction of the object is generated at step 120, and this control signal is supplied to the focus position control circuit 15 as the control signal S_{C2} at step 108.

Each time the control signal S_{C2} is supplied to the focus position control circuit 15 at step 108, it is determined at step 121 whether the next field of the colour signal has come by detecting vertical synchronizing signals (not shown) contained in the auto-focus control circuit 10. If so, the routine goes back to the beginning (step 100).

While the properly-focused positions of blue light L_B and red light L_R are respectively displaced towards the zoom lens 2 and the image pick-up element 3 from the properly-focused position P of green light L_G by the predetermined very short lengths P_B and P_R in the above-mentioned embodiment, in other embodiments the properly-focused positions of blue light L_B and red light L_R may be respectively moved towards the image pick-up element 3 and the zoom lens 2.

The present invention can be applied to an apparatus that utilizes a lens with no zoom function. If so, the zoom amount detecting circuit 17 is not necessary, which simplifies the overall arrangement of the apparatus.

In the above-described embodiment the focus position information is detected on the basis of the amplitude values of the three colour signals S_B , S_G and S_R as described above, however, the present invention can be modified such that the amplitude values of, for example, the blue and red signals S_B and S_R only are employed to detect the focus position information.

While in the above embodiment the position of the zoom lens 2 is adjusted on the basis of the amplitude

values of the colour signals as described above, the present invention is not limited to the above-mentioned embodiment and less advantageous embodiments can simultaneously use the prior art wobbling method.

While in the above embodiment the position of the zoom lens 2 is adjusted on the basis of the focus position information as described above, the invention can be applied to a wide variety of applications, for example, in which focus position information, is displayed.

The invention can also be applied to other apparatus such as an image pick-up apparatus, a camera and so on that are used to pick up a still picture.

Claims

1. Automatic focus control apparatus (1) characterized by:
 - lens means (2) having chromatic aberration;
 - means (3) for converting an optical signal obtained through said lens means (2) to an electrical signal;
 - means (4,5) for processing said electrical signal to obtain a plurality of primary colour signals;
 - means (7,8) for detecting the amplitude level of each of said primary colour signals;
 - means (10) for generating a control signal according to levels of said primary colour signals derived from said level detecting means (7,8); and
 - means (15) for controlling the position of said lens in response to said control signal.
2. Apparatus (1) according to a claim 1 wherein said primary colour signals are red, green and blue signals.
3. Apparatus (1) according to claim 1 or claim 2 wherein said detecting means (7,8) comprises separate series circuits of a filter (7) and a level detector (8) provided for each of said primary colour signals, and first switch means (9) for selectively supplying an output of said level detectors (8) to said control signal generating means (10).
4. Apparatus (1) according to claim 3 wherein said control signal generating means (10) normalizes the outputs of said level detectors (8) by respectively dividing said outputs by the amplitude levels of the corresponding primary colour signals supplied by said processing means (4,5).
5. Apparatus (1) according to claim 4 further comprising second switch means (11) for selectively supplying said primary colour signals to said control signal generating means (10).
6. Apparatus (1) according to claim 5 further comprising analogue-to-digital converter means (12,13) for separately converting the outputs of said level detectors (8) and the output of said second switch means (11).
7. Apparatus (1) according to claim 6 wherein said control signal generating means (10) includes stored information representing level

orders of said primary colour signals versus each focus point of said primary colours, and wherein said control signal is generated according to said stored information.

8. Apparatus (1) according to any one of the preceding claims wherein said lens means (2) is a zoom lens (2) and said apparatus (1) further comprises means (17) for detecting the zoom amount of said zoom lens (2), the output of said zoom amount detecting means (17) being

supplied to said control signal generating means (10) for compensation of said control signal.

9. Apparatus (1) according to claim 2 further comprising a matrix circuit (6) for converting said red, green and blue primary colour signals to a luminance signal and colour difference signals.

5

10

15

20

25

30

35

40

45

50

55

60

65

FIG. 1




FIG. 3




FIG. 4





FIG. 5

	A	B	P	C	D
S'_B	I	I	II	III	III
S'_G	II	I	I	I	II
S'_R	III	III	II	I	I

FIG. 6





DOCUMENTS CONSIDERED TO BE RELEVANT			EP 89303042.9
Category	Citation of document with indication, where appropriate, of relevant passages	Relevant to claim	CLASSIFICATION OF THE APPLICATION (Int. Cl.4)
A	<u>DE - A1 - 3 443 558</u> (CANON) * Fig. 1 *	1,2,9	H 04 N 5/232 G 03 B 3/10
A	<u>EP - A2 - 0 260 990</u> (VICTOR COMP.) * Abstract; fig. 1 *	1,8	
			TECHNICAL FIELDS SEARCHED (Int. Cl.4)
			H 04 N 5/00 H 04 N 9/00 G 03 B 3/00
The present search report has been drawn up for all claims			
Place of search VIENNA		Date of completion of the search 13-06-1989	Examiner BENISCHKA
CATEGORY OF CITED DOCUMENTS			
X : particularly relevant if taken alone Y : particularly relevant if combined with another document of the same category A : technological background O : non-written disclosure P : intermediate document		T : theory or principle underlying the invention E : earlier patent document, but published on, or after the filing date D : document cited in the application L : document cited for other reasons & : member of the same patent family, corresponding document	

THIS PAGE BLANK (USPTO)

**This Page is Inserted by IFW Indexing and Scanning
Operations and is not part of the Official Record**

BEST AVAILABLE IMAGES

Defective images within this document are accurate representations of the original documents submitted by the applicant.

Defects in the images include but are not limited to the items checked:

- ☒ BLACK BORDERS
- ☐ IMAGE CUT OFF AT TOP, BOTTOM OR SIDES
- ☐ FADED TEXT OR DRAWING
- ☐ BLURRED OR ILLEGIBLE TEXT OR DRAWING
- ☐ SKEWED/SLANTED IMAGES
- ☐ COLOR OR BLACK AND WHITE PHOTOGRAPHS
- ☐ GRAY SCALE DOCUMENTS
- ☐ LINES OR MARKS ON ORIGINAL DOCUMENT
- ☐ REFERENCE(S) OR EXHIBIT(S) SUBMITTED ARE POOR QUALITY
- ☐ OTHER: _____

IMAGES ARE BEST AVAILABLE COPY.

As rescanning these documents will not correct the image problems checked, please do not report these problems to the IFW Image Problem Mailbox.

THIS PAGE BLANK (USPTO)